



Support: The Specifications

1500W DC ATX P4 Power Supply (10-18VDC)

Now you can power every PC in your car. 1,5kW power is giving you all possibilities ! The ATX connector has 24 pins.

| Dimensions<br>Weight<br>Input Voltage Range                              | 150mm[W] × 370mm[L] × 86mm[H] ATX PS/2 size<br>6 kgs<br>10 - 18VDC |
|--|--|
| Output Power<br>maximum  | 1500W  |
| Output Power<br>maximum (rails)  | +3.3V : 35A<br>+5.0V : 35A<br>+12.0V : 123A                        |
| Remote sensing   | +5V and +3.3V  |
| Over Power Protection Load over 130%±10% of max. output power : shutdown |  |
| Over Voltage<br>Protection   | +5V, +12V & +3.3V Auto-recovery                                    |
| Short Circuit<br>Protection  | Main outputs shutdown and latch off                                |
| Over Temperature<br>Protection   | OTP Level is set at 110°C  |
| Operating<br>Temperature   | -20°C ~ +70°C  |
| Storage Temperature  | -20°C~+80°C  |
| Cooling  | Build-in 2x 80x80x25mm Ball Bearing Fan                            |

2549.00 EUR incl. 19% VAT, plus shipping

• STC-121500H



Note : Minimum power of 60W must be drawn at system startup time !